Eaton 93PS 8-40kW Standard UPS Technical Specification

CONSTRUCTION	8KW	10kW	15kW	20kW	30kW	40kW		
Model	93PS- 8(20)	93PS-10(20)	93PS-15(20)	93PS-20(20)	93PS-30(40)	93PS-40(40)		
Initial Rating (Initial Rating)	8kVA/8kW	10kVA/10kW	15kVA/10kW	20kVA/20kW	30kVA/30kW	40kVA/40kW		
Initial Internal Redundancy Rating	-	-	-	-	15kW N+1	20kW N+1		
Configured Upgradability								
External Paralleling	Up to 4 units with Hot Sync® technology							
UPS Topology	Double Conversion, IGBT Converters, three level Inverter							
Performance Classification	VFI-SS-111							
UPS Dimensions: W x D x H (mm)	335 x 750 x 1300 480 x 750 x 1750							
Weight (kg) excluding batteries	116	116	116	116	208	208		
Weight per Module (kg)	_	_	_	_	200	200		
Degree of protection	28 kg (<25kg w/o fan panel & DC capacitors) IP20							
Cabinet Colour	Black; RAL 9005							
Switchgear (Internal)	Optional Maintenance Bypass Switch							
Cable Entry								
Mean Time To Repair (MTTR)	Rear <30 minutes							
	<30 minutes	•						
ENVIRONMENT	5 (6	5. 5500: d						
Ambient storage temperature	Range of -25 to +55°C in the protective package							
Ambient service temperature	Power electronics part: 0 to 40°C without de-rating Battery part: +5 to 25°C without reducing battery life							
Maximum service altitude	1000m above sea level. Maximum 2000m with 1% de-rating per each additional 100m above 1000m							
Relative humidity	5 to 95%, no condensation allowed							
Acoustic noise at 1m	<60 dBA in double conversion, <47 dBA in ESS							
Electromagnetic Compatibility	Immunity and emission to IEC/EN 62040-2							
USER INTERFACE & COMMUNICATI	ONS							
Display	5" Touchscr	een Colour disp	lay					
Standard Communication Ports		t, 1 x EPO input JSB, 1 x RS232	t (NC/NO), 1 x Relay output (NO/NC), 5 x Building Alarm					
Optional Communication Ports	Mini-Slot ca	rds: Web/SNMP	, Relay/RS232,	Industrial Relay	, ModBus, Powe	er Xpert		
ELECTRICAL INPUT CHARACTERIS	TICS		-					
Earthing system compatibility	TN, TT							
Rated input voltage and voltage tolerance	Rectifier: 230/400Vac nominal (220/380, 240/415 Selectable) Tolerance: 187/324-276/480V (-18%,+20%) at 100% load Bypass: 230/400Vac nominal (220/380, 240/415 Selectable) Tolerance: 196/340-253/438V (-15%,+10% of nominal)							
Operating frequency / tolerance	50 or 60 Hz, user configurable; Tolerance 40-72 Hz							
Input power factor	0.99pf							
Inrush current	<100% of rated current. Rectifier ramp-up 5A/s (default), configurable, min. 1A/s							
Number of phases	3 phases +			(**************************************	<u> </u>			
Rated input r.m.s. current 380V	13 A	16 A	24 A	32 A	48 A	63 A		
400V	12 A	15 A	23 A	30 A	46 A	61 A		
415V	12 A	15 A	22 A	29 A	44 A	58 A		
Maximum input r.m.s. current	15 A	19 A	29 A	38 A	57 A	76 A		
Bypass input current @400V Recommended/Maximum (rms)	12/17A	15/21A	22/32A	29/42A	44/64A	59/85A		
Input current distortion at rated input current (THDi)	<5%	<4%	<3%					



Eaton 93	3PS 8	-40kW S	tandard L	JPS Techr	ical Spec	cification			
CONSTRUCTION		8KW	10kW	15kW	20kW	30kW	40kW		
ELECTRICAL OUTPUT CHA	RACTER	ISTICS - NOF	RMAL MODE			•			
Rated output voltage		220/380V; 2	30/400V; 240/4	15V, configurab	e				
Output voltage variation		<1% static load, 4% with 100ms recovery from 100% load step							
Crest factor		3:1							
Rated output frequency		50Hz (default) or 60Hz							
Output frequency variation		±0.1 Hz							
Slew rate		0.8-1 Hz/s							
Total output voltage distortion		<1% for linear load; <5% for non-linear load							
Voltage unbalance at referenc unbalanced load	е	<0.5%							
Output current limitation, short capability	-circuit	72 A, 300ms 144 A				144 A, 300ms			
Overload capability without by	pass	10 min 102-110% load, 60 sec 111-125% load, 10 sec 126-150% load load					ms >150%		
Overload capability with bypas	SS	Continuous < 125% load, 20 ms 1000% load							
Load power factor range	0.8 lagging	to 0.8 leading w	ithout de-rating						
Range of frequency sync with	bypass	±4Hz as def	ault. User settal	ble 0.5 to 5 Hz					
ELECTRICAL OUTPUT CHAI	RACTER	ISTICS - STO	RED ENERGY	MODE					
Transfer to/from stored energy	,	No break							
Rated output voltage 220/380V; 230/400V; 240/415V, three phase					е				
Output voltage variation		<1%							
Crest factor	3:1								
Rated output frequency		50Hz (default) or 60Hz							
Output frequency variation		± 0.1Hz							
Total voltage harmonic distorti	on								
100% linear load		<1%							
100% non-linear load		<5%							
Short circuit capability	72 A, 300ms 144 A, 300ms								
	10 min 102-110% load								
Overload capability		60 sec 111-125% load							
		10 sec 126-150% load							
		300 ms >150% load							
Load power factor range		0.8 lagging	to 0.8 leading w	ithout de-rating					
EFFICIENCY									
Efficiency in double- conversion, rated linear load	100%	95.9%	96.1%	96.0%	95.9%	96.1%	95.7%		
	75%	95.5%	95.8%	96.1%	96.1%	96.1%	96.0%		
	50%	94.5%	95.1%	95.8%	96.1%	95.9%	96.1%		
	25%	91.5%	92.5%	94.3%	95.1%	94.6%	95.5%		
Heat dissipation in double	100%	328 W	390 W	600 W	820 W	1170 W	1720 W		
conversion	75%	270 W	315 W	489 W	585 W	878 W	1200 W		
	50%	220 W	245 W	315 W	390 W	615 W	780 W		
	25%	170 W	188 W	214 W	245 W	405 W	450 W		
Efficiency in ESS, rated linear load	100%	98.2%	98.4%	98.6%	98.6%	98.8%	98.8%		
		98.2%	98.4%	98.6%	98.6%	98.8%	98.8%		
	75%						98.8%		
	50%	96.9%	97.5%	98.1%	98.3%	98.4%			
	25%	94.6%	95.5%	96.9%	97.3%	97.4%	98.0%		



CONSTRUCTION	8KW	10kW	15kW	20kW	30kW	40kW	
BYPASS CHARACTERISTICS							
Automatic bypass	Static bypass switch, continuously rated, no break transfer						
Bypass voltage rating	220/380V; 230/400V; 240/415V tolerance -15% / +10% of rated voltage						
Automatic bypass thyristor i ² t value: Pre-arc i ² t Total clearing i ² t	36	<u>andard</u> 60 A²s 00 A²s	<u>super-sized</u> 1900 A²s 7100 A²s		1900 A²s 7100 A²s		
Back-feed protection	Standard in	Standard internal back-feed contactor					
Required external bypass protective fuse, recommended rating	Circuit breaker C32			Circuit breaker C 63			
Manual bypass switch (internal)	Optional						
ESS (Energy Saver System) MODE	CHARACTER	ISTICS					
Performance Classification	VFD, transferring to VFI (Double Conversion mode) if limits are exceeded						
Transfer time to double conversion	Mains available: No break; Mains failure: Typically 2 ms						
Acceptable output voltage variation	± 10% of nominal voltage, default						
Acceptable output freq. variation	± 4 Hz, default						
Storm Detection	UPS locks into double-conversion mode when three power line disturbance have forced the unit to double-conversion three times (user adjustable) within a one-hour period (use adjustable)						
High Alert mode		ay on double-cor lly return to oper		hour (user adjus	table), after wh	ich the unit w	
BATTERY							
Battery nominal voltage	336V (28 x 12V, 168 Cells) or 384V (32 x 12V, 192 Cells) or 480V (40 x 12V, 240 Cells)						
Float charge voltage	2.30V per Cell						
Maximum charge voltage	240 x 2.35V = 564V						
Battery technology	Valve Regulated Lead Acid, 5 or 10 year design life						
Maximum Charging current (Default/Maximum)		5A/25A		10A	/50A		
Restored energy time to 90%	Typically 10	x Discharge tin	ne (dependent o	n configuration)			
Battery recharge profile	Advanced Battery Management (ABM®) = 90% resting, 10% floating/charging						
Battery cutt off voltage	1.67 to 1.75 VPC, Configurable or automatic (load adaptive)						
Battery start option	Yes						

